



BROTHER KH-950i FAIR-ISLE **en una hoja Mylar**

2 Colores Fair-Isle (Entretejido).

Ejemplo: Hoja N° 4 - Diseño N° 4-16.

(Puedes crear tus diseños de punto propios en una hoja Mylar vacía).

Pasos a seguir (PASO A):

- 1) Tejer unas líneas de tejido jersey/liso.
- 2) Dejar el carro en el lado izdo. de la tricotosa pasado el sensor.
- 3) Con la tricotosa apagada.
(Introducir la hoja Mylar en la ranura del lector hasta colocarla en la línea "**SET LINE**", anota las cuatro posiciones del gráfico).
- 4) Encender la tricotosa.
- 5) **M**
(La luz de "PATTERN No" tiene que estar encendida).
- 6) **901**
(Introducir el número deseado para cargar nuestro diseño; es a partir de la posición: 901, 902, 903...
- 7) **M**
(Se enciende la luz inferior)
(1) + # (N° de posición del comienzo del gráfico en vertical)
M
(Se enciende la luz superior)
(2) + # (N° de posición del final del gráfico en vertical)
M
(Se enciende la luz izquierda)
(3) + # (N° de posición del comienzo del gráfico en horizontal)
M
(Se enciende la luz derecha):
(4) + # (N° de posición del final del gráfico en horizontal)
M
- 8) **CF**
- 9) Carro principal en **KC**.
- 10) Deslizar el carro a la derecha.
(Se seleccionarán las agujas)
- 11) Pulsar **MC** que es el botón superior central del carro principal.
- 12) Enhebrar segundo color de hilo en el alimentador de hilo **B**.
- 13) Tejer.

En el caso que lo anterior no lo puedas hacer debido a que da **ERROR el Paso A**, realiza los siguiente pasos previamente:

Pasos a seguir (**PASO B**):

- 1) Encender la tricotosa
- 2) 777
- 3) M
- 4) 901 (Introducir el número que os ha dado error en el anterior PASO A)
- 5) M
- 6) 1
- 7) M
- 8) 1
- 9) M
- 10) CF
(La hoja Mylar será leída completa por el lector, esperar a que termine).
- 11) Apagar la tricotosa.
- 12) Y comenzar de nuevo en el PASO A.

En el caso que lo anterior no lo puedas hacer debido a que da **ERROR el Paso B**, realiza los siguiente pasos:

Pasos a seguir (**PASO C**):

- 1) Encender la tricotosa
- 2) 888
- 3) M
(Esperar a que termine el borrado de memoria, esto puede tardar hasta 30 segundos. Esto no borra los patrones predefinidos de la 950i.)
- 4) Apagar la tricotosa y esperar unos segundos hasta volver a encender.
- 5) Ir a la Paso A y en caso que no os funcione ir a la Paso B.

Cómo borrar una posición de memoria para volver a cargar otro gráfico.

En este ejemplo, borrar la posición o celda 901.

- 1) 777
- 2) M
901 (Introducir el número de posición para borrar)
- 3) CR
(Esperar unos segundos a que termine)
- 4) CR
(La luz verde "READY" se enciende y está ya borrada dicha posición).



BROTHER KH-950i FAIR-ISLE **on a Mylar Card**

2 Colours Fair-Isle.

Example: Card/Sheet No 4 - Stitch Design No 4-16.

(You can create your own stitch designs on an empty Mylar Card).

Steps to follow (**STEP A**):

-
- 1) Knit a few rows of jersey stitch.
 - 2) Place the carriage on the left side of the machine once the sensor is overpassed.
 - 3) With the Knitting Machine off.
(Insert the Mylar Sheet into the slot of the reader until it is positioned on the "SET LINE", write down the four positions of the graph).
 - 4) Switch on the Knitting Machine.
 - 5) **M**
(The "PATTERN No" light must be on).
 - 6) **901**
(Enter the desired number to load our design; it is from the position: 901, 902, 903....)
 - 7) **M**
(The lower light comes on)
(1) + # (Position no. of the beginning of the vertical chart)
M
(The top light is switched on)
(2) + # (Position no. at the end of the vertical chart)
M
(The left-hand light comes on)
(3) + # (Position no. of the beginning of the graph horizontally)
M
(The right-hand light comes on)
(4) + # (Position no. of the end of the chart horizontally)
M
 - 8) **CF**
 - 9) The carriage with the selector in **KC**.
 - 10) Slide the carriage to the right for the first needle selection.
 - 11) Activate the **MC** button on the main carriage (Top centre button)
 - 12) Thread the second colour yarn into the thread feeder **B**.
 - 13) Knit!

In case you cannot do the above because of an **ERROR in Step A**, perform the following steps first:

Steps to follow (**STEP B**):

- 13) Switch on the Knitting Machine.
- 14) 777
- 15) M
- 16) 901 (Enter the number that gave you the error in the previous STEP A)
- 17) M
- 18) 1
- 19) M
- 20) 1
- 21) M
- 22) CF
(The Mylar sheet will be read in its entirety by the reader, wait for it to finish).
- 23) Switch off the Knitting Machine.
- 24) And start again at STEP A.

In case you are unable to do the above because of an **ERROR in Step B**, perform the following steps:

Steps to follow (**STEP C**):

- 6) Switch on the Knitting Machine.
- 7) 888
- 8) M
(Wait for the memory erase to finish, this may take up to 30 seconds. This does not erase the 950i's preset patterns).
- 9) Switch off the knitting machine and wait a few seconds before switching it on again.
- 10) Go to Step A and in case it doesn't work, go to Step B.

How to delete a memory location in order to reload another chart.

In this example, delete position or cell 901.

- 5) 777
- 6) M
901 (Enter position number for deletion)
- 7) CR
(Wait a few seconds for it to finish)
- 8) CR
(The green "READY" light comes on and the position is already deleted).